
MSKSEMI















ESD

TVS

TSS

MOV

GDT

PLED

Broduct data sheet



Feature

44W peak pulse power per line ($t_P = 8/20\mu s$)

SOD-923 package

Replacement for MLV(0402)

Bidirectional configurations

Response time is typically < 1ns

Low clamping voltage

RoHS compliant

Transient protection for data lines to

IEC61000-4-2(ESD) ±30KV(air), ±30KV(contact);

IEC61000-4-4 (EFT) 40A (5/50ns)

Mechanical Characteristics

Lead finish:100% matte Sn(Tin)


Mounting position: Any

Qualified max reflow temperature:260°C

Device meets MSL 1 requirements

Pure tin plating: 7 ~ 17 um

Pin flatness:≤3mil



SOD-923

Electrical characteristics per line@25℃ (unless otherwise specified)


Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Peak Reverse Working Voltage	V_{RWM}				3.3	٧
Breakdown Voltage	V_{BR}	I _t = 1mA	5			٧
Reverse Leakage Current	I _R	V _{RWM} = 5V T=25°C			2.5	μA
Maximum Reverse Peak Pulse Current	I _{PP}			2.3		Α
Clamping Voltage	Vc	Ipp MAX, tp =8/20 μs			19	٧
Junction Capacitance	Cj	V _R =0V f = 1MHz		12	18	pF

Absolute maximum rating@25℃

Rating	Symbol	Value	Units
Peak Pulse Power (t _p =8/20µs)	P _{pp}	44	W
Operating Temperature	TJ	-55 to +150	$^{\circ}$ C
Storage Temperature	T _{STG}	-55 to +150	${\mathbb C}$


Electronics Parameter

Symbol	Parameter		
V _{RWM}	Peak Reverse Working Voltage		
I _R	Reverse Leakage Current @ V _{RWM}		
V _{BR}	Breakdown Voltage @ I⊤		
Ι _Τ	Test Current		
I _{PP}	Maximum Reverse Peak Pulse Current		
Vc	Clamping Voltage @ I _{PP}		
P _{PP}	Peak Pulse Power		
Сл	Junction Capacitance		
I _F	Forward Current		
V _F	Forward Voltage @ I _F		






PACKAGE MECHANICAL DATA



Dim	Millimeters			Inches		
	Min	Nom	Max	Min	Nom	Max
Α	0.36	0.40	0.43	0.014	0.016	0.017
b	0.15	0.20	0.25	0.006	0.008	0.010
С	0.07	0.12	0.17	0.003	0.005	0.007
D	0.75	0.80	0.85	0.030	0.031	0.033
E	0.55	0.60	0.65	0.022	0.024	0.026
HE	0.95	1.00	1.05	0.037	0.039	0.041
L	0.05	0.10	0.15	0.002	0.004	0.006

Suggested Pad Layout



Dimensions: Millimeters

REEL SPECIFICATION

P/N	PKG	QTY
MSESD9B3.3ST5G	SOD-923	8000

Semiconductor



Attention

- Any and all MSKSEMI Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your MSKSEMI Semiconductor representative nearest you before using any MSKSEMI Semiconductor products described or contained herein in such applications.
- MSKSEMI Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all MSKSEMI Semiconductor products described or contained herein.
- Specifications of any and all MSKSEMI Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- MSKSEMI Semiconductor. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with someprobability. It is possiblethat these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits anderror prevention circuitsfor safedesign, redundant design, and structural design.
- In the event that any or all MSKSEMI Semiconductor products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from theauthorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of MSKSEMI Semiconductor.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. MSKSEMI Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringementsof intellectual property rights or other rightsof third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. Whendesigning equipment, referto the "Delivery Specification" for the MSKSEMI Semiconductor productthat you intend to use.